






17. Special Functions Configuring subtitles

Opening the menu

People with a hearing impairment can make use of the subtitle function.



By default, the "Subtitle" function has to be activated first of all via the TV menu.

Activating subtitles

- Call up the TV menu with the MENU button.
- Use the red button  to open the "Configuration" menu.
- Use the cursor key  to change to the menu option "Initial programme position".
- Use the respective numeric key to select the menu option "Subtitle".
- In the settings window, use the  button to set the "Subtitle" function to "on".
- If desired, a language can be selected here.
- Press the **OK** button to save the new settings.
- Press the **EXIT** button to close the "TV menu".

Displaying subtitles - see next page.


MENU



EXIT



Menü aufrufen



17. Special Functions Displaying subtitles

If a TV program has subtitles, they can be displayed by pressing the green button.

A program marked in this manner comes with subtitles.

Displaying subtitles:

- Press the **F2** button. Press **F2** briefly to run the function programmed for the **F2** button (see Chapter 18. "Programming function buttons"). Press **F2** for approx. 3 seconds and the max. possible selection will be displayed.
- Use the numeric key **0** to call up the "Subtitle" function.
- Use the cursor keys **▼ ▲** to make a selection (if this is offered by the broadcasting station or the program).

F2



3




Special functions 2

- 1 Normal/Speech
- 2 Language of progr.
- 3 Subtitle

- 9 Timer overview
- 0 Direct recording



The broadcasting station is responsible for offering and displaying subtitles.

1 Off

▶ 2 Deutsch

3 English

34. Software-Update

Menü aufrufen

Update function for the TV software via satellite (Astra)

Requirements:

- DVB-S module for SAT reception via ASTRA.
- An MH module with USB interface (MPEG4-Decoder).
- A station, which is transmitted by the Astra satellite, has to be saved in the station table.
- No programmed timer recording within the next 120 minutes.



In the configuration menu u DVB-S u Software update you have the following options to configure the update search for TV software:

- Off
- Immediate
- Always when in standby

• Update search Off (factory setting)

The automatic search and installation of TV software is deactivated.

MENU




Menü aufrufen

34. Software-Update

• Immediate update search

Press the **OK** button to start the search for new TV software immediately.


Once the search has been completed, the Version function reveals whether a more recent version of the TV software is available.



OK

Use the cursor key ► to go to the menu item **Update Info** and press **OK**. You can view the available changes in the Update Info window.

Close the **Update Info** window by pressing **EXIT**, then select the menu option Installation using the cursor key ▼ and press the **OK** button.



The **New software version available** window appears.

New software version available.

Do you want install the software?

Ⓢ Yes

Ⓢ No

Ⓢ carry out later

34. Software-Update

Yes:

A new window appears asking you once again whether you want to install the software now.

Carry out later:

The window disappears and reappears when you turn your TV on or off again.

No:

The reminder window does not appear again as long as there is no TV software available that is more recent than the one rejected.

Now press the green  button (**Yes**). A new window opens.

Installation lasts up to a few hours.
Don't switch off device during this time !
Switch off will be done automatically after update.

Installation now?



Yes



No



carry out later

Press the green  button again, the software download will then commence.

You can cancel the current software download by pressing the **EXIT** button.



Software download is in progress.



24 %

EXIT Cancel

34. Software-Update

The software is installed automatically after the download is finished.




Under no circumstances should the device be switched off !

Once the installation is finished, the device is automatically switched off and goes into standby mode.

Programming of TV set is carrying out.

Device must not switched off during this time!



If you want to start the update and the following message appears:

This means that you have programmed a timer recording that is set to begin within the next 120 minutes.



Software update not possible
in case of recording.

carry out later

EXIT Cancel

• Update search always when in standby

After going into standby mode, the device searches for new TV software.

If TV software is available, which is more recent than the software installed on your TV, this is shown in a window that appears after turning the device on or off.

TV-Menü

★ ★ ★

Bild und Ton

● AV Geräte

● Sendertabelle

● Timer

● **Konfiguration**

F1↑

0	Funktion für F2
9	Funktion für F1
8	EURO-Buchsen
7	DVB-C ²⁾
6	DVB-T ²⁾
5	DVB-S ²⁾
4	Analog-TV ²⁾
3	Land
2	Sprache
1	Bedienung

1	Software-Update
6	Allgem. Einstellungen
5	Manuelle Suche
4	Automatische Suche
3	Satellit B
2	Astra 19,2°
1	Antennenanlage


- + Option wählen.
 Bei „sofort“ wird die Suche
 mit OK aktiviert ansonsten
 Speicherung.
 Zurück mit **MENU**

Updatesuche
immer Standby





- ① Service Center
- ② Trainings Center
- ③ Verwaltung und Entwicklung
- ④ Lager/Versand
- ⑤ Mecablitz Produktion
- ⑥ TV Produktion
- ⑦ Kunststofftechnik



Metz - Werke GmbH & Co. KG - Zirndorf bei Nürnberg

Kernkompetenzen in den Bereichen Elektronik sowie Kunststofftechnik bilden den Ursprung für den ausgezeichneten Ruf der Metz-Werke. Er hat sich im Laufe vieler Jahrzehnte weltweit aufgebaut.

Metz bietet Qualität Made in Germany:
Consumer Electronics, Photo Electronics, Kunststofftechnik.

Metz-Werke GmbH & Co. KG
Postfach 1267, D-90506 Zirndorf

Fon: +49 911 - 9706 0
Fax: +49 911 - 9706 340

www.metz.de
info@metz.de

Errors excepted. Subject to changes.
610 45 0143.A1

Ⓜ Printed in Germany

Metz - always first class.

